

UNITED STATES PATENT APPLICATION

**LOW-TEMPERATURE GROWN HIGH QUALITY ULTRA-
THIN CoTiO₃ GATE DIELECTRICS**

INVENTORS

Kie Y. Ahn

of Chappaqua, NY

and

Leonard Forbes

of Corvallis, OR

Schwegman, Lundberg, Woessner, & Kluth, P.A.

1600 TCF Tower

121 South Eighth Street

Minneapolis, Minnesota 55402

ATTORNEY DOCKET 1303.030US1

Client Ref. No. 01-0486

Drafting Atty.: David Peterson

LOW-TEMPERATURE GROWN HIGH QUALITY ULTRA-THIN CoTiO_3 GATE DIELECTRICS

Field of the Invention

The invention relates to semiconductor devices and device fabrication. Specifically, the invention relates to gate oxide layers of transistor devices and their method of fabrication.

Background of the Invention

5 In the semiconductor device industry, particularly in the fabrication of transistors, there is continuous pressure to reduce the size of devices such as transistors. The ultimate goal is to fabricate increasingly smaller and more reliable integrated circuits (ICs) for use in products such as processor chips, mobile telephones, or memory devices such as
10 DRAMs. The smaller devices are frequently powered by batteries, where there is also pressure to reduce the size of the batteries, and to extend the time between battery charges. This forces the industry to not only design smaller transistors, but to design them to operate reliably with lower power supplies.

A common configuration of a transistor is shown in Figure 1. While the
15 following discussion uses Figure 1 to illustrate a transistor from the prior art, one skilled in the art will recognize that the present invention could be incorporated into the transistor shown in Figure 1 to form a novel transistor according to the invention. The transistor 100 is fabricated in a substrate 110 that is typically silicon, but could be fabricated from other semiconductor materials as well. The transistor 100 has a first
20 source/drain region 120 and a second source/drain region 130. A body region 132 is located between the first source/drain region and the second source/drain region, the body region 132 defining a channel of the transistor with a channel length 134. A gate dielectric, or gate oxide 140 is located on the body region 132 with a gate 150 located over the gate oxide. Although the gate dielectric can be formed from materials other than

oxides, the gate dielectric is typically an oxide, and is commonly referred to as a gate oxide. The gate may be fabricated from polycrystalline silicon (polysilicon) or other conducting materials such as metal may be used.

In fabricating transistors to be smaller in size and reliably operating on lower power supplies, one important design criteria is the gate oxide 140. A gate oxide 140, when operating in a transistor, has both a physical gate oxide thickness and an equivalent oxide thickness (EOT). The equivalent oxide thickness quantifies the electrical properties, such as capacitance, of a gate oxide 140 in terms of a representative physical thickness. EOT is defined as the thickness of a theoretical SiO₂ layer that describes the actual electrical operating characteristics of the gate oxide 140 in the transistor 100. For example, in traditional SiO₂ gate oxides, a physical oxide thickness may be 5.0 nm, but due to undesirable electrical effects such as gate depletion, the EOT may be 6.0 nm. A gate oxide other than SiO₂ may also be described electrically in terms of an EOT. In this case, the theoretical oxide referred to in the EOT number is an equivalent SiO₂ oxide layer. For example, SiO₂ has a dielectric constant of approximately 4. An alternate oxide with a dielectric constant of 20 and a physical thickness of 100 nm would have an EOT of approximately 20 nm = (100 * (4/20)), which represents a theoretical SiO₂ gate oxide.

Lower transistor operating voltages and smaller transistors require thinner equivalent oxide thicknesses (EOTs). A problem with the increasing pressure of smaller transistors and lower operating voltages is that gate oxides fabricated from SiO₂ are at their limit with regards to physical thickness and EOT. Attempts to fabricate SiO₂ gate oxides thinner than today's physical thicknesses show that these gate oxides no longer have acceptable electrical properties. As a result, the EOT of a SiO₂ gate oxide 140 can no longer be reduced by merely reducing the physical gate oxide thickness.

Attempts to solve this problem have led to interest in gate oxides made from oxide materials other than SiO₂. Certain alternate oxides have a higher dielectric constant (k), which allows the physical thickness of a gate oxide 140 to be the same as existing SiO₂ limits or thicker, but provides an EOT that is thinner than current SiO₂ limits.

A problem that arises in forming an alternate oxide layer on the body region of a transistor is the process in which the alternate oxide is formed on the body region. Recent studies show that the surface roughness of the body region has a large effect on the electrical properties of the gate oxide, and the resulting operating characteristics of the transistor. The leakage current through a physical 1.0 nm gate oxide increases by a factor of 10 for every 0.1 increase in the root-mean-square (RMS) roughness. In forming an alternate oxide layer on the body region of a transistor, a thin layer of the alternate material to be oxidized (typically a metal) must first be deposited on the body region. Current processes for depositing a metal or other alternate layer on the body region of a transistor are unacceptable due to their effect on the surface roughness of the body region.

Figure 2A shows a surface 210 of a body region 200 of a transistor. The surface 210 in the Figure has a high degree of smoothness, with a surface variation 220. Figure 2B shows the body region 200 during a conventional sputtering deposition process stage. During sputtering, particles 230 of the material to be deposited bombard the surface 210 at a high energy. When a particle 230 hits the surface 210, some particles adhere as shown by particle 235, and other particles cause damage as shown by pit 240. High energy impacts can throw off body region particles 215 to create the pits 240. A resulting layer 250 as deposited by sputtering is shown in Figure 2C. The deposited layer/body region interface 255 is shown following a rough contour created by the sputtering damage. The surface of the deposited layer 260 also shows a rough contour due to the rough interface 255.

In a typical process of forming an alternate material gate oxide, the deposited layer 250 is oxidized to convert the layer 250 to an oxide material. Existing oxidation processes do not, however, repair the surface damage created by existing deposition methods such as sputtering. As described above, surface roughness has a large influence on the electrical properties of the gate oxide and the resulting transistor.

What is needed is an alternate material gate oxide that is more reliable at existing EOTs than current gate oxides. What is also needed is an alternate material gate oxide with an EOT thinner than conventional SiO_2 . What is also needed is an alternative

material gate oxide with a smooth interface between the gate oxide and the body region. Because existing methods of deposition are not capable of providing a smooth interface with an alternate material gate oxide, what is further needed is a method of forming an alternate material gate oxide that maintains a smooth interface.

5 Additionally, at higher process temperatures, any of several materials used to fabricate the transistor, such as silicon, can react with other materials such as metals or oxygen to form unwanted silicides or oxides. At high process temperatures, materials such as dopants can also migrate to unwanted areas, changing the desired structure or composition profile that is desired. What is needed is a lower temperature process of
10 forming gate oxides that prevents migration and the formation of unwanted byproduct materials.

Summary of the Invention

A method of forming a gate oxide on a surface such as a transistor body region is
15 shown where a metal alloy layer is deposited by thermal evaporation on the body region. The metal alloy layer is then oxidized to convert the metal alloy layer to a gate oxide. In one embodiment, the metal alloy layer includes cobalt (Co) and titanium (Ti). One embodiment of the invention uses an electron beam source to evaporate the metal alloy layer onto the body region of the transistor. The oxidation process in one embodiment
20 utilizes a krypton(Kr)/oxygen (O₂) mixed plasma process.

In addition to the novel process of forming a gate oxide layer, a transistor formed by the novel process exhibits novel features that may only be formed by the novel process. Thermal evaporation deposition of a metal alloy layer onto a body region of a transistor preserves an original smooth surface roughness of the body region in contrast to
25 other prior deposition methods that increase surface roughness. The resulting transistor fabricated with the process of this invention will exhibit a gate oxide/body region interface with a surface roughness variation as low as 0.6 nm.

These and other embodiments, aspects, advantages, and features of the present invention will be set forth in part in the description which follows, and in part will

become apparent to those skilled in the art by reference to the following description of the invention and referenced drawings or by practice of the invention. The aspects, advantages, and features of the invention are realized and attained by means of the instrumentalities, procedures, and combinations particularly pointed out in the appended
5 claims.

Brief Description of the Drawings

Figure 1 shows a common configuration of a transistor.

Figure 2A shows a smooth surface of a body region of a transistor.

10 Figure 2B shows a deposition process according to the prior art.

Figure 2C shows a deposited film on a body region according to the prior art.

Figure 3A shows a deposition process according to the invention.

Figure 3B shows a magnified view of a deposited film on a body region from Figure 3A.

Figure 4A shows a deposited film on a body region according to the invention.

15 Figure 4B shows a partially oxidized film on a body region according to the invention.

Figure 4C shows a completely oxidized film on a body region according to the invention.

Figure 5 shows a perspective view of a personal computer.

Figure 6 shows a schematic view of a central processing unit.

Figure 7 shows a schematic view of a DRAM memory device.

20

Detailed Description of the Preferred Embodiments

In the following detailed description of the invention, reference is made to the accompanying drawings which form a part hereof, and in which is shown, by way of illustration, specific embodiments in which the invention may be practiced. In the
25 drawings, like numerals describe substantially similar components throughout the several views. These embodiments are described in sufficient detail to enable those skilled in the art to practice the invention. Other embodiments may be utilized and structural, logical, and electrical changes may be made without departing from the scope of the present invention. The terms wafer and substrate used in the following description include any

structure having an exposed surface with which to form the integrated circuit (IC) structure of the invention. The term substrate is understood to include semiconductor wafers. The term substrate is also used to refer to semiconductor structures during processing, and may include other layers that have been fabricated thereupon. Both wafer
5 and substrate include doped and undoped semiconductors, epitaxial semiconductor layers supported by a base semiconductor or insulator, as well as other semiconductor structures well known to one skilled in the art. The term conductor is understood to include semiconductors, and the term insulator or dielectric is defined to include any material that is less electrically conductive than the materials referred to as conductors.

10 The term “horizontal” as used in this application is defined as a plane parallel to the conventional plane or surface of a wafer or substrate, regardless of the orientation of the wafer or substrate. The term “vertical” refers to a direction perpendicular to the horizontal as defined above. Prepositions, such as “on”, “side” (as in “sidewall”), “higher”, “lower”, “over” and “under” are defined with respect to the conventional plane
15 or surface being on the top surface of the wafer or substrate, regardless of the orientation of the wafer or substrate. The following detailed description is, therefore, not to be taken in a limiting sense, and the scope of the present invention is defined only by the appended claims, along with the full scope of equivalents to which such claims are entitled.

Figure 3A shows an electron beam evaporation technique to deposit a material on
20 a surface such as a body region of a transistor. In Figure 3A, a substrate 310 is placed inside a deposition chamber 300. The substrate in this embodiment is masked by a first masking structure 312 and a second masking structure 314. In this embodiment, the unmasked region 316 includes a body region of a transistor, however one skilled in the art will recognize that other semiconductor device structures may utilize this process. Also
25 located within the deposition chamber 300 is an electron beam source 330, and a target 334. In one embodiment, a single electron beam source is used and a single target is used. However multiple targets and electron beam sources could be used. In one embodiment, a single target is used that includes an alloy material of two elements. In alternative embodiments, more than two elements are included in an alloy target.

Although in this embodiment, an electron beam evaporation technique is used, it will be apparent to one skilled in the art that other thermal evaporation techniques can be used without departing from the scope of the invention.

During the evaporation process, the electron beam source 330 generates an
5 electron beam 332. The electron beam hits the target 334 and heats a portion of the target enough to cause the surface of the target to evaporate. The evaporated material 336 is then distributed throughout the chamber 300, and the material 336 deposits on surfaces that it contacts, such as the exposed body region 316. The depositing material builds up to form a layer 320 of material that is chemically the same as the target 334.

10 In one embodiment, the evaporation process is performed at a background pressure of approximately 1×10^{-7} torr. In one embodiment the target is preheated for several minutes before the evaporation process begins. One typical evaporation rate for this process includes a rate of 0.5 to 1.0 nm/second. A device such as a quartz crystal microbalance is used to assist monitoring of the deposition process in one embodiment.
15 Using a metal evaporation process as described above, a packing density of the layer 320 approaches 1.0. In other words, the layers 320 generated by this process will have close to zero lattice defects.

In one embodiment of the invention, the deposited material layer 320 includes a multiple metal alloy layer. In one embodiment of the invention, the deposited material
20 layer 320 includes cobalt (Co) and titanium (Ti). In one embodiment of the invention, the target is a single target of cobalt and titanium alloy. In one embodiment, two targets containing one element each are used to form the layer 320. One advantage of the thermal evaporation process is the high purity targets that are available for the process. Zone refined targets have purity as high as 99.9999%. Additionally, the evaporation
25 process itself further purifies the target materials thus increasing the final purity of the layer 320 beyond even the target purity. The more violent nature of other deposition methods tends to mix impurities into the deposited layer during deposition. Therefore a uniquely pure layer 320 and further, a uniquely pure layer oxide is possible using this novel method.

The choice of materials for oxidation is based on the properties of the oxide formed. Considerations included the thermodynamic stability of the oxide with silicon, the diffusion coefficient of the oxide at high processing temperatures such as 1000° K, the lattice match of the oxide with silicon, the dielectric constant of the oxide, and the conduction band offset of the oxide. In one embodiment, the dielectric constant is approximately 40, which is approximately ten times the dielectric constant of SiO₂. In one embodiment, the deposited material layer 320 is substantially amorphous. A lower presence of grain boundaries in the substantially amorphous material layer 320 reduces the leakage current through the final gate oxide. Although the amorphous form is preferred, the materials chosen for oxidation, such as cobalt and titanium are also acceptable in crystalline form.

A thermal evaporation process such as the electron beam evaporation technique described above does not cause the surface damage that is inherent in other deposition techniques such as the sputtering technique shown in Figure 2B. This allows a very thin layer of material to be deposited on a body region of a transistor, while maintaining a smooth interface. A thermal evaporation process such as the electron beam evaporation technique described above also allows low processing temperatures that inhibit the formation of unwanted byproducts such as silicides and oxides. In one embodiment, the thermal evaporation is performed with a substrate temperature between approximately 100 and 150° C.

Figure 3B shows a magnified view of the body region 316 and the deposited layer 320 from Figure 3A. The interface 340 is shown with a roughness variation 346. The surface of the deposited layer 348 is also shown with a similar surface roughness. One possible surface variation 346 would be an atomic layer variation. In atomic smoothness, the greatest difference in surface features is between a first atomic layer as indicated by layer 342 and a second atomic layer 344. The thermal evaporation deposition technique described above preserves atomic smoothness such as is shown in Figure 3B, however other acceptable levels of surface roughness greater than atomic smoothness will also be preserved by the thermal evaporation technique.

Figures 4A-4C show a low temperature oxidation process that is used in one embodiment to convert the deposited layer 320 into a gate oxide. A deposited material layer 410 is shown in Figure 4A on a substrate surface 400. The layer 410 forms an interface 420 with the substrate surface 400, and the layer 410 has an outer surface 430.

5 The layer 410 in this embodiment is deposited over a body region of a transistor, however the layer may be deposited on any surface within the scope of the invention.

In Figure 4B, the layer 410 is in the process of being oxidized. In one embodiment, the oxidation process includes a krypton/oxygen mixed plasma oxidation process. The mixed plasma process generates atomic oxygen or oxygen radicals in contrast to molecular oxygen or O₂ used in conventional thermal oxidation. The atomic oxygen in this embodiment is generated by microwave excitation of the krypton and oxygen environment to form a high-density plasma. The atomic oxygen is introduced to the layer from all exposed directions as indicated by arrows 440, creating an oxide portion 450. The atomic oxygen continues to react with the layer and creates an oxidation interface 422. As the reaction progresses, atomic oxygen diffuses through the oxide portion 450 and reacts at the oxidation interface 422 until the layer is completely converted to an oxide of the deposited material layer. Figure 4C shows the resulting oxide layer 450 which spans a physical thickness 452 from the outer surface 430 to the interface 420.

20 In one embodiment, the processing variables for the mixed plasma oxidation include a low ion bombardment energy of less than 7 eV, a high plasma density above 10¹²/cm³ and a low electron temperature below 1.3 eV. In one embodiment, the substrate temperature is approximately 400 °C. In one embodiment, a mixed gas of 3% oxygen with the balance being krypton at a pressure of 1 Torr is used. In one embodiment, a microwave power density of 5 W/cm² is used. In one embodiment, the oxidation process provides a growth rate of 2 nm/min.

The low substrate temperature of the mixed plasma oxidation process described above allows the deposited layer to be oxidized at a low temperature, which inhibits the formation of unwanted byproducts such as silicides and oxides. The low temperature also

inhibits migration of elements such as dopant species. Low migration preserves designed atomic distribution profiles, thus allowing more advanced device designs and providing higher reliability in existing device designs. The mixed plasma process in one embodiment is performed at approximately 400° C in contrast to prior thermal oxidation processes that are performed at approximately 1000° C. The mixed plasma oxidation process has also been shown to provide improved thickness variation on silicon (111) surfaces in addition to (100) surfaces. Although the low temperature mixed plasma process above describes the formation of alternate material oxides, one skilled in the art will recognize that the process can also be used to form SiO₂ oxide structures.

10 In one embodiment, a cobalt-titanium alloy forms an oxide comprised of CoTiO₃. The cobalt-titanium oxide CoTiO₃ exhibits a dielectric constant of approximately 40, which allows for a thinner EOT than conventional SiO₂. In addition to the stable thermodynamic properties inherent in the oxides chosen, the novel process used to form the oxide layer is performed at lower temperatures than the prior art. This inhibits
15 reactions with the silicon substrate or other structures, and inhibits unwanted migration of elements such as dopants.

A transistor made using the novel gate oxide process described above will possess several novel features. By creating an oxide material with a higher dielectric constant (k) and controlling surface roughness during formation, a gate oxide can be formed with an
20 EOT thinner than 2 nm. A thicker gate oxide that is more uniform, and easier to process can also be formed with the alternate material oxide of the present invention, the alternate material gate oxide possessing an EOT equivalent to the current limits of SiO₂ gate oxides. The smooth surface of the body region is preserved during processing, and a resulting transistor will have a smooth interface between the body region and the gate
25 oxide with a surface roughness on the order of 0.6 nm.

Transistors created by the methods described above may be implemented into memory devices and information handling devices as shown in Figure 5, Figure 6, and Figure 7 and as described below. While specific types of memory devices and computing

devices are shown below, it will be recognized by one skilled in the art that several types of memory devices and information handling devices could utilize the invention.

A personal computer, as shown in Figures 5 and 6, include a monitor 500, keyboard input 502 and a central processing unit 504. The processor unit typically includes microprocessor 606, memory bus circuit 608 having a plurality of memory slots 612(a-n), and other peripheral circuitry 610. Peripheral circuitry 610 permits various peripheral devices 624 to interface processor-memory bus 620 over input/output (I/O) bus 622. The personal computer shown in Figures 5 and 6 also includes at least one transistor having a gate oxide according to the teachings of the present invention.

Microprocessor 606 produces control and address signals to control the exchange of data between memory bus circuit 608 and microprocessor 606 and between memory bus circuit 608 and peripheral circuitry 610. This exchange of data is accomplished over high speed memory bus 620 and over high speed I/O bus 622.

Coupled to memory bus 620 are a plurality of memory slots 612(a-n) which receive memory devices well known to those skilled in the art. For example, single in-line memory modules (SIMMs) and dual in-line memory modules (DIMMs) may be used in the implementation of the present invention.

These memory devices can be produced in a variety of designs which provide different methods of reading from and writing to the dynamic memory cells of memory slots 612. One such method is the page mode operation. Page mode operations in a DRAM are defined by the method of accessing a row of a memory cell arrays and randomly accessing different columns of the array. Data stored at the row and column intersection can be read and output while that column is accessed. Page mode DRAMs require access steps which limit the communication speed of memory circuit 608. A typical communication speed for a DRAM device using page mode is approximately 33 MHZ.

An alternate type of device is the extended data output (EDO) memory which allows data stored at a memory array address to be available as output after the addressed column has been closed. This memory can increase some communication speeds by

allowing shorter access signals without reducing the time in which memory output data is available on memory bus 620. Other alternative types of devices include SDRAM, DDR SDRAM, SLDRAM and Direct RDRAM as well as others such as SRAM or Flash memories.

5 Figure 7 is a block diagram of an illustrative DRAM device 700 compatible with memory slots 612(a-n). The description of DRAM 700 has been simplified for purposes of illustrating a DRAM memory device and is not intended to be a complete description of all the features of a DRAM. Those skilled in the art will recognize that a wide variety of memory devices may be used in the implementation of the present invention. The
10 example of a DRAM memory device shown in Figure 7 includes at least one transistor having a gate oxide according to the teachings of the present invention.

Control, address and data information provided over memory bus 620 is further represented by individual inputs to DRAM 700, as shown in Figure 7. These individual representations are illustrated by data lines 702, address lines 704 and various discrete
15 lines directed to control logic 706.

As is well known in the art, DRAM 700 includes memory array 710 which in turn comprises rows and columns of addressable memory cells. Each memory cell in a row is coupled to a common wordline. Additionally, each memory cell in a column is coupled to a common bitline. Each cell in memory array 710 includes a storage capacitor and an
20 access transistor as is conventional in the art.

DRAM 700 interfaces with, for example, microprocessor 606 through address lines 704 and data lines 702. Alternatively, DRAM 700 may interface with a DRAM controller, a micro-controller, a chip set or other electronic system. Microprocessor 606 also provides a number of control signals to DRAM 700, including but not limited to,
25 row and column address strobe signals RAS and CAS, write enable signal WE, an output enable signal OE and other conventional control signals.

Row address buffer 712 and row decoder 714 receive and decode row addresses from row address signals provided on address lines 704 by microprocessor 606. Each unique row address corresponds to a row of cells in memory array 710. Row decoder 714

includes a wordline driver, an address decoder tree, and circuitry which translates a given row address received from row address buffers 712 and selectively activates the appropriate wordline of memory array 710 via the wordline drivers.

Column address buffer 716 and column decoder 718 receive and decode column address signals provided on address lines 704. Column decoder 718 also determines when a column is defective and the address of a replacement column. Column decoder 718 is coupled to sense amplifiers 720. Sense amplifiers 720 are coupled to complementary pairs of bitlines of memory array 710.

Sense amplifiers 720 are coupled to data-in buffer 722 and data-out buffer 724. Data-in buffers 722 and data-out buffers 724 are coupled to data lines 702. During a write operation, data lines 702 provide data to data-in buffer 722. Sense amplifier 720 receives data from data-in buffer 722 and stores the data in memory array 710 as a charge on a capacitor of a cell at an address specified on address lines 704.

During a read operation, DRAM 700 transfers data to microprocessor 606 from memory array 710. Complementary bitlines for the accessed cell are equilibrated during a precharge operation to a reference voltage provided by an equilibration circuit and a reference voltage supply. The charge stored in the accessed cell is then shared with the associated bitlines. A sense amplifier of sense amplifiers 720 detects and amplifies a difference in voltage between the complementary bitlines. The sense amplifier passes the amplified voltage to data-out buffer 724.

Control logic 706 is used to control the many available functions of DRAM 700. In addition, various control circuits and signals not detailed herein initiate and synchronize DRAM 700 operation as known to those skilled in the art. As stated above, the description of DRAM 700 has been simplified for purposes of illustrating the present invention and is not intended to be a complete description of all the features of a DRAM.

Those skilled in the art will recognize that a wide variety of memory devices, including but not limited to, SDRAMs, SLDRAMs, RDRAMs and other DRAMs and SRAMs, VRAMs and EEPROMs, may be used in the implementation of the present invention. The DRAM implementation described herein is illustrative only and not intended to be
5 exclusive or limiting.

Conclusion

Thus has been shown a gate oxide and method of fabricating a gate oxide that produce a more reliable and thinner equivalent oxide thickness. Gate oxides formed
10 cobalt-titanium alloy are thermodynamically stable such that the gate oxides formed will have minimal reactions with a silicon substrate or other structures during any later high temperature processing stages. CoTiO_3 in particular has been shown to provide excellent electrical and thermodynamic properties. In addition to the stable thermodynamic properties inherent in the gate oxide of the invention, the process shown is performed at
15 lower temperatures than the prior art. This inhibits reactions with the silicon substrate or other structures, and inhibits unwanted migration of elements such as dopants.

Transistors and higher level ICs or devices have been shown utilizing the novel gate oxide and process of formation. The higher dielectric constant (k) oxide materials shown in one embodiment are formed with an EOT thinner than 2 nm, e.g. thinner than
20 possible with conventional SiO_2 gate oxides. A thicker gate oxide that is more uniform, and easier to process has also been shown with at EOT equivalent to the current limits of SiO_2 gate oxides.

A novel process of forming a gate oxide has been shown where the surface smoothness of the body region is preserved during processing, and the resulting transistor
25 has a smooth interface between the body region and the gate oxide with a surface roughness on the order of 0.6 nm. This solves the prior art problem of poor electrical properties such as high leakage current, created by unacceptable surface roughness.

Although specific embodiments have been illustrated and described herein, it will be appreciated by those of ordinary skill in the art that any arrangement which is

calculated to achieve the same purpose may be substituted for the specific embodiment shown. This application is intended to cover any adaptations or variations of the present invention. It is to be understood that the above description is intended to be illustrative, and not restrictive. Combinations of the above embodiments, and other embodiments 5 will be apparent to those of skill in the art upon reviewing the above description. The scope of the invention includes any other applications in which the above structures and fabrication methods are used. The scope of the invention should be determined with reference to the appended claims, along with the full scope of equivalents to which such claims are entitled.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217